

1. General description

High voltage, high speed, planar passivated NPN power switching transistor with integrated anti-parallel emitter-collector diode in a TO92 plastic package.

2. Features and benefits

- High typical DC current gain
- Fast switching
- High voltage capability
- Integrated anti-parallel E-C diode

3. Applications

- Compact fluorescent lamps (CFL)
- Low power electronic lighting ballasts
- Off-line self-oscillating power supplies (SOPS) for battery charging



4. Quick reference data

Table 1. Quick reference data

Symbol	Parameter	Conditions	Values			Unit
Absolute maximum rating						
V_{CESM}	collector-emitter peak voltage	$V_{BE} = 0\text{ V}$	700			V
I_C	collector current	DC	1.5			A
P_{tot}	total power dissipation	$T_{lead} \leq 25\text{ °C}$; Fig. 1	2.1			W
Symbol	Parameter	Conditions	Min	Typ	Max	Unit
Static characteristics						
h_{FE}	DC current gain	$I_C = 0.5\text{ A}$; $V_{CE} = 2\text{ V}$; $T_j = 25\text{ °C}$	8	17	25	

5. Pinning information

Table 2. Pinning information

Pin	Symbol	Description	Simplified outline	Graphic symbol
1	B	base	 <p>TO-92 (SOT54)</p>	 <p>sym131</p>
2	C	collector		
3	E	emitter		

6. Ordering information

Table 3. Ordering information

Type number	Package Name	Orderable part number	Packing method	Small packing quantity	Package version	Package issue date
PHD13003C	TO92	PHD13003C,412	Bulk	2000	SOT54	14-Nov-2013
PHD13003C	TO92	PHD13003C,126	Reel	2000	SOT54 wide pitch	14-Nov-2013

7. Marking

Table 4. Marking codes


Type number	Marking codes
PHD13003C	D13003C

8. Limiting values

Table 5. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134).

Symbol	Parameter	Conditions	Values	Unit
V_{CESM}	collector-emitter peak voltage	$V_{BE} = 0\text{ V}$	700	V
V_{CBO}	collector-base voltage	$I_E = 0\text{ A}$	700	V
V_{CEO}	collector-emitter voltage	$I_B = 0\text{ A}$	400	V
I_C	collector current	DC	1.5	A
I_{CM}	peak collector current		3	A
I_B	base current	DC	0.75	A
I_{BM}	peak base current		1.5	A
P_{tot}	total power dissipation	$T_{lead} \leq 25\text{ °C}$; Fig. 1	2.1	W
T_{stg}	storage temperature		-65 to 150	°C
T_j	junction temperature		150	°C
V_{EBO}	emitter-base voltage	$I_C = 0\text{ A}$; $I(\text{Emitter}) = 10\text{ mA}$	9	V



9. Thermal characteristics

Table 6. Thermal characteristics

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
$R_{th(j-lead)}$	thermal resistance from junction to lead	Fig. 2	-	-	60	K/W
$R_{th(j-a)}$	thermal resistance from junction to ambient	in free air; printed-circuit board mounted; lead length = 4 mm	-	150	-	K/W




Fig. 2. Transient thermal impedance from junction to lead as a function of pulse width

10. Characteristics

Table 7. Characteristics

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
Static characteristics						
I_{CES}	collector-emitter cut-off current	$V_{BE} = 0\text{ V}; V_{CE} = 700\text{ V}$	-	-	1	mA
		$V_{BE} = 0\text{ V}; V_{CE} = 700\text{ V}; T_j = 100^\circ\text{C}$	-	-	5	mA
I_{CEO}	collector-emitter cut-off current	$V_{CE} = 400\text{ V}; I_B = 0\text{ A}; T_{lead} = 25^\circ\text{C}$	-	-	0.1	mA
I_{EBO}	emitter-base cut-off current	$V_{EB} = 9\text{ V}; I_C = 0\text{ A}; T_{lead} = 25^\circ\text{C}$	-	-	1	mA
V_{CEOSus}	collector-emitter sustaining voltage	$I_B = 0\text{ A}; I_C = 1\text{ mA}; L_C = 25\text{ mH}; T_{lead} = 25^\circ\text{C};$ Fig. 3 ; Fig. 4	400	-	-	V
V_{CEsat}	collector-emitter saturation voltage	$I_C = 0.5\text{ A}; I_B = 0.1\text{ A}; T_{lead} = 25^\circ\text{C}$	-	-	0.5	V
		$I_C = 1\text{ A}; I_B = 0.25\text{ A}; T_{lead} = 25^\circ\text{C}$	-	-	1	V
		$I_C = 1.5\text{ A}; I_B = 0.5\text{ A}; T_{lead} = 25^\circ\text{C}$	-	-	1.5	V
V_{BEsat}	base-emitter saturation voltage	$I_C = 0.5\text{ A}; I_B = 0.1\text{ A}; T_{lead} = 25^\circ\text{C}$	-	-	1	V
		$I_C = 1\text{ A}; I_B = 0.25\text{ A}; T_{lead} = 25^\circ\text{C}$	-	-	1.2	V
V_F	forward voltage	$I_F = 0.5\text{ A}; T_j = 25^\circ\text{C}$	-	-	1.5	V
h_{FE}	DC current gain	$I_C = 0.5\text{ A}; V_{CE} = 2\text{ V}; T_j = 25^\circ\text{C}$	8	17	25	
		$I_C = 1\text{ A}; V_{CE} = 2\text{ V}; T_j = 25^\circ\text{C}$	5	9	15	
Dynamic characteristics						
t_{on}	turn-on time	$I_C = 1\text{ A}; I_{Bon} = 0.2\text{ A}; I_{Boff} = -0.2\text{ A}; R_L = 75\ \Omega; T_{lead} = 25^\circ\text{C};$ resistive load; Fig. 5 ; Fig. 6	-	-	1	μs
t_s	storage time	$I_C = 1\text{ A}; I_{Bon} = 0.2\text{ A}; I_{Boff} = -0.2\text{ A}; R_L = 75\ \Omega; T_{lead} = 25^\circ\text{C};$ resistive load; Fig. 5 ; Fig. 6	-	-	4	μs
		$I_C = 1\text{ A}; I_{Bon} = 0.2\text{ A}; V_{BB} = -5\text{ V}; L_B = 1\ \mu\text{H}; T_{lead} = 25^\circ\text{C};$ inductive load; Fig. 7 ; Fig. 8	-	0.8	-	μs
t_f	fall time	$I_C = 1\text{ A}; I_{Bon} = 0.2\text{ A}; I_{Boff} = -0.2\text{ A}; R_L = 75\ \Omega; T_{lead} = 25^\circ\text{C};$ resistive load; Fig. 5 ; Fig. 6	-	-	0.7	μs
		$I_C = 0.5\text{ A}; I_{Bon} = 0.1\text{ A}; V_{BB} = -5\text{ V}; L_B = 1\ \mu\text{H}; T_{lead} = 25^\circ\text{C};$ inductive load; Fig. 7 ; Fig. 8	-	0.1	-	μs




Fig. 3. Test circuit for collector-emitter sustaining voltage





Fig. 4. Oscilloscope display for collector-emitter sustaining voltage test waveform



$V_{IM} = -6\text{ V to } +8\text{ V}; V_{CC} = 250\text{ V}; t_p = 20\text{ }\mu\text{s};$
 $\delta = t_p/T = 0.01.$
 R_B and R_L calculated from I_{Con} and I_{Bon} requirements

Fig. 5. Test circuit for resistive load switching





Fig. 6. Switching times waveforms for resistive load



$V_{CC} = 300\text{ V}$; $V_{BB} = -5\text{ V}$; $L_C = 200\text{ }\mu\text{H}$; $L_B = 1\text{ }\mu\text{H}$.

Fig. 7. Test circuit for inductive load switching







Fig. 8. Switching times waveforms for inductive load

11. Package outline



SOT54 PACKAGE OUTLINE





SOT54
Bulk Pack - 412





SOT54 LEADS ON CIRCLE
Bulk Pack - 112




SOT54 WIDE PITCH
Tape/ Reel Pack - 116
Ammo Pack - 126



SOT54 LEAD BEND L01
Bulk Pack - 412




SOT54 LEAD BEND L02
Bulk Pack - 412



Remark: Detailed dimensions refer to POD drawing.

Plastic single-ended leaded(through hole) package; 3 leads

TO92



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	3.300	3.700	0.130	0.146
A1	1.100	1.400	0.043	0.055
b	0.380	0.550	0.015	0.022
c	0.360	0.510	0.014	0.020
D	4.300	4.700	0.169	0.185
E	4.300	4.700	0.169	0.185
e	1.270 TYP.		0.050 TYP.	
e1	2.440	2.640	0.096	0.104
L	14.100	14.500	0.555	0.571

12. Legal information

Data sheet status

Document status [1][2]	Product status [3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

- [1] Please consult the most recently issued document before initiating or completing a design.
- [2] The term 'short data sheet' is explained in section "Definitions".
- [3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL <http://www.ween-semi.com>.

Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. WeEn Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local WeEn Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between WeEn Semiconductors and its customer, unless WeEn Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the WeEn Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, WeEn Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. WeEn Semiconductors takes no responsibility for the content in this document if provided by an information source outside of WeEn Semiconductors.

In no event shall WeEn Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, WeEn Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of WeEn Semiconductors.

Right to make changes — WeEn Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — WeEn Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an WeEn Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. WeEn Semiconductors and its suppliers accept no liability for inclusion and/or use of WeEn Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Quick reference data — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. WeEn Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using WeEn Semiconductors products, and WeEn Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the WeEn Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

WeEn Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using WeEn Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). WeEn does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Non-automotive qualified products — Unless this data sheet expressly states that this specific WeEn Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. WeEn Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without WeEn Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond WeEn Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies WeEn Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond WeEn Semiconductors' standard warranty and WeEn Semiconductors' product specifications.

Translations — A non-English (translated) version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

13. Contents

- 1. General description..... 1
- 2. Features and benefits 1
- 3. Applications 1
- 4. Quick reference data 1
- 5. Pinning information..... 2
- 6. Ordering information..... 2
- 7. Marking..... 2
- 8. Limiting values 3
- 9. Thermal characteristics 5
- 10. Characteristics..... 6
- 11. Package outline 9
- 12. Legal information 11
- 13. Contents 13

© WeEn Semiconductors Co., Ltd. 2021. All rights reserved

For more information, please visit: <http://www.ween-semi.com>
For sales office addresses, please send an email to: salesaddresses@ween-semi.com
Date of release: 10 October 2021
